



Features:

- Simple and professional
- Mode 3, Type 2
- Up to 22 kW
- Simple installation
- Activation with:
 - Button
 - Key
 - **RFID** tag

Charge EV at:

- Your garage
- Private car parking
- Company territory
- Fleet parking

HomeBox is designed to be simple and cost effective solution for fast, up to 22 kW EV charging. HomeBox can be used in garages, parking lots and other private areas, where no authentication is required.

With integrated over current and leakage current protections it can be installed as a standalone unit.

Bright red status light on the Start/Stop buttons is visible even in direct sunlight. Integrated energy meter with LED back-light is convenient for separating your EV from domestic energy bill.



HomeBox is designed to be used at home or office with top industry quality, ensuring long life and high reliability.

HomeBox is available in 3—Phase 16A or 32A versions, depending on power source provided.

For more information visit: www.ElintaCharge.com

HomeBox Technical specifications



Sockettype	
Mode 2—CEE 7/4 (Schuko)	\checkmark
Mode 3—IEC 62196 (Type 2)	\checkmark
Inputpower	
3-phase: 400 V/AC 50 Hz 16 — 32 A	\checkmark
Output power (optional)	
1-phase 230 V/AC 16 A (3,7 kW)	\checkmark
1-phase 230 V/AC 32 A (7,2 kW)	\checkmark
3-phase 400 V/AC 16 A (11 kW)	\checkmark
3-phase 400 V/AC 32 A (22 kW)	\checkmark
Energy meter	
Digital with backlight	\checkmark
Operational temperature	
-30 °C to +50 °C	\checkmark
Protection	
Degree of protection	IP54
Impact protection	IK08
Stainless housing	plastic
UV resistant	\checkmark
Certificates	
CE	\checkmark

Communication (opti	onal)	
3G - Elios.cloud - OCPP		\checkmark
WiFi - Elios.cloud - OCPP		\checkmark
Ethernet - Elios.cloud - OC	PP	\checkmark
Power management syster	n	optional
Safety		
RFID identification		optional
Charging cable locking		optional
Overcurrent protection		\checkmark
Leakage current protectior	ı	\checkmark
Dimensions		
Weight	6 kg	
Depth x width x height	140 x 256 x	k 400 mm





Terminalo g. 3, Biruliskiu k., Karmelavos sen., LT-54469 Kauno raj., Lithuania

www.ElintaCharge.com

charge@elinta.lt mob. +370 653 66633 mob. +370 615 71604

Model	Power/Option
EM-HB-T2-3.6	3.6 kW
EM-HB-T2-7.2	7.2 kW
EM-HB-T2-11	11 kW
EM-HB-T2-22	22 kW
EM-HB-T2-XX-K	Key access
EM-HB-T2-XX-RFID	RFID access
EM-HB-T2-XX-3G	RFID access with 3G communication
EM-HB-T2-XX-WIFI	RFID access with WiFi communication
EM-HB-T2-XX-ETH	RFID access with Ethernet communication